

UNITED STATES PATENT APPLICATION

of

Donald A. Ice

for

**METHODS FOR MANUFACTURING OPTICAL
MODULES USING LEAD FRAME CONNECTORS**

WORKMAN NYDEGGER
A PROFESSIONAL CORPORATION
ATTORNEYS AT LAW
1000 EAGLE GATE TOWER
60 EAST SOUTH TEMPLE
SALT LAKE CITY, UTAH 84111

METHODS FOR MANUFACTURING OPTICAL MODULES USING LEAD FRAME CONNECTORS

BACKGROUND OF THE INVENTION

1. Related Application

[0001] This application claims the benefit of U.S. Provisional Patent Application Serial No. 60/548,485, filed February 27, 2004, which is incorporated herein by reference.

2. The Field of the Invention

[0002] The present invention relates generally to optical transceiver modules. More specifically, the present invention relates to methods of manufacturing optical transceiver modules using lead frame connectors that connect an optical sub-assembly to a printed circuit board in the optical transceiver module.

3. Background and Relevant Art

[0003] Optical transceivers are used to transmit and receive optical signals from an optical network and to enable electrical network components to interface with and communicate over optical networks. Many optical transceivers are modular and are designed in accordance with industry standards that define mechanical aspects of the transceivers, form factors, optical and electrical requirements, and other characteristics and requirements of the transceivers. For example the Small Form-Factor Module Multi-Source Agreement (SFF MSA), the Small Form-Factor Pluggable Module Multi-Source Agreement (SFP MSA) and the 10 Gigabit Small Form Factor Pluggable Module Multi-Source Agreement (XFP MSA) Revision 3.1 define such standards and are incorporated herein by reference.

[0004] The basic optical components of conventional transceivers include a transmitter optical sub-assembly (TOSA) and a receiver optical sub-assembly (ROSA). The TOSA receives electrical signals from a host device via circuitry of the transceiver module and generates a corresponding optical signal that is then transmitted to a remote node in an optical network. Conversely, the ROSA receives an incoming optical signal and outputs a corresponding electrical signal that can then be used or processed by the host device.

[0005] The electrical connections between the optical sub-assemblies and a printed circuit board (PCB) in the transceiver module have various electrical and mechanical requirements. One of the most common electrical connection components used in conventional optical transceiver modules is a flexible printed circuit board, or "flex circuit," that connects the rigid printed circuit board of the module to leads associated with the TOSA or ROSA. Flex circuits have several advantages, including good electrical performance and radio frequency response and the ability to take up tolerances in the modules and to withstand stresses that arise during manufacture and operation of the modules. Examples of flex circuits used in optical transceiver modules are described in U.S. Patent Application Serial No. 10/409,837, filed April 9, 2003, which is incorporated herein by reference. The foregoing patent application also illustrates other components of optical transceiver modules, such as TOSAs and ROSAs, and includes other general information regarding optical transceiver modules that is useful as background material for the invention described herein.

[0006] While flex circuits have been widely used in recent years in optical transceiver modules, flex circuits represent a significant portion of the costs and labor required to manufacture transceiver modules. As the price of transceiver modules drops, the costs

associated with flex circuits continue to represent an increasing proportion of the overall costs of transceiver modules.

[0007] Other approaches to connecting optical sub-assemblies to printed circuit boards have been introduced in recent years. For example, the leads protruding from TOSAs and ROSAs can be bent into a configuration that enables the leads to be directly soldered or otherwise connected to the printed circuit board. This technique is often less expensive than the use of flex circuits, but can lead to unfavorable RF response due to the inability to carefully control impedances. In addition, machining leads of TOSAs and ROSAs introduces reliability risks due to the likelihood of damaging glass or other fragile portions of header assemblies in TOSAs and ROSAs that enclose the lasers and photodetectors, respectively.

[0008] Because of the possibility of damaging the TOSAs and ROSAs and poor electrical performance, bending leads to enable the optical sub-assemblies to be directly connected to the printed circuit board is not suitable for many transceiver modules. This approach is particularly unsuitable for relatively high-speed transceiver modules, in which the RF response of the conductors is more important.

BRIEF SUMMARY OF EMBODIMENTS OF THE INVENTION

[0009] The present invention relates to methods for manufacturing or assembling optical transceiver modules using lead frame connectors that electrically and mechanically connect optical sub-assemblies to printed circuit boards. The lead frame connectors enable optical sub-assemblies to be connected to the printed circuit board in optical transceiver modules in a reliable and inexpensive manner. The use of such lead frame connectors eliminates the need for flexible printed circuit boards that have been used in conventional transceiver modules.

[0010] According to one embodiment, the lead frame connector includes a stamped and bent conductive lead structure that is encased within an insert injection molded plastic casing. The plastic casing provides electrical insulation for the conductors in the lead frame as well as mechanical support for the finished component. The lead frame connectors connect to the leads associated with the optical sub-assemblies. The lead frame connectors also can be surface mounted onto the printed circuit board to establish connectivity between the optical sub-assembly and the printed circuit board. The lead frame connectors can be adapted for use with transmitter optical sub-assemblies and receiver optical sub-assemblies, and can have any necessary number of leads.

[0011] To assemble an optical transceiver module, the lead frame connector is aligned with the leads that protrude from the back end of the corresponding optical sub-assembly (OSA). The leads pass through corresponding holes in the lead frame connector and the leads are soldered to the conductors of the lead frame assembly. Once the soldering has been performed, the combined OSA and lead frame connector becomes a surface mount device that can then be mounted to the PCB.

[0012] In certain embodiments of the invention, the process of connecting the combined ROSA and lead frame connector to the PCB does not require epoxy reinforcement and avoids alignment handling issues that have been experienced in conventional methods of connecting optical sub-assemblies to PCBs using, for instance, flexible printed circuit boards.

[0013] The foregoing, together with other features and advantages of the present invention, will become more apparent when referred to the following specification, claims and accompanying drawings.

WORKMAN NYDEGGER
A PROFESSIONAL CORPORATION
ATTORNEYS AT LAW
1000 EAGLE GATE TOWER
60 EAST SOUTH TEMPLE
SALT LAKE CITY, UTAH 84111

BRIEF DESCRIPTION OF THE DRAWINGS

[0014] In order that the manner in which the above-recited and other advantages and features of the invention are obtained, a more particular description of the invention briefly described above will be rendered by reference to specific embodiments thereof which are illustrated in the appended drawings. Understanding that these drawings depict only typical embodiments of the invention and are not therefore to be considered limiting of its scope, the invention will be described and explained with additional specificity and detail through the use of the accompanying drawings in which:

[0015] Figure 1a illustrates a ROSA and a corresponding lead frame connector that is constructed according to an embodiment the invention.

[0016] Figure 1b illustrates a TOSA and a corresponding lead frame connector that is constructed according to an embodiment of the invention.

[0017] Figure 2a further illustrates the ROSA lead frame connector of Figure 1a.

[0018] Figure 2b illustrates a stamped and bent lead frame without the plastic casing that is insert injection molded around the lead frame.

[0019] Figures 2c-2f illustrates various views of the ROSA lead frame connector of Figure 1a.

[0020] Figure 3a further illustrates the TOSA lead frame connector of Figure 1b.

[0021] Figure 3b illustrates a stamped and bent lead frame without the plastic casing that is insert injection molded around the lead frame.

[0022] Figures 3c-3f illustrates various views of the TOSA lead frame connector of Figure 1b.

[0023] Figures 4a and 4b are perspective views of opposite sides of a printed circuit board that has lead frame connectors attached thereto.

WORKMAN NYDEGGER
A PROFESSIONAL CORPORATION
ATTORNEYS AT LAW
1000 EAGLE GATE TOWER
60 EAST SOUTH TEMPLE
SALT LAKE CITY, UTAH 84111

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0024] The present invention relates methods of manufacturing optical transceiver modules using lead frame connectors that electrically and mechanically connect optical sub-assemblies to printed circuit boards in optical transceiver modules. According to one embodiment, the lead frame connector is fabricated using an insert injection molding process applied to a reel-to-reel stamped lead frame ribbon. The lead frame connectors connect to the leads associated with the optical sub-assemblies. The lead frame connectors also can be surface mounted onto the printed circuit board to establish connectivity between the optical sub-assembly and the printed circuit board.

[0025] The lead frame connectors of the invention provide several advantages compared to the use of flex circuits or other conventional techniques. Compared to flex circuits, the lead frame connector components are significantly less expensive. In addition, the process of manufacturing a transceiver module using lead frame connectors is more automated and requires less labor. Compared to simply bending the leads of the optical sub-assemblies to permit direct connection to a PCB, the lead frame connectors have significantly better electrical performance and RF response. Moreover, there is no significant risk of damaging the fragile portions of the optical sub-assemblies during the process of connecting the optical sub-assemblies to the PCB.

1. Lead Frame Connector Structure

[0026] Figure 1a illustrates a ROSA 10 and a corresponding lead frame connector 12 that is constructed according to an embodiment the invention. ROSAs typically have five leads 14, and the lead frame connector 12 of Figure 1a has five corresponding electrical contacts 16 and

leads 18. Figure 1b illustrates a TOSA 20 and a corresponding lead frame connector 22 that is constructed according to an embodiment of the invention. TOSAs typically have four leads 24, and the lead frame connector 22 of Figure 1b has four corresponding electrical contacts 26 and leads 28. Although the lead frame connectors of Figures 1a and 1b are shown with four and five electrical contacts and leads, respectively, the principles of the invention disclosed herein can be applied to form lead frame connectors that have substantially any number of required electrical contacts and leads.

[0027] Figures 2a-2g and 3a-3g show various views of the lead frame connectors 12 and 22 of Figures 1a and 1b. U.S. Patent Application Serial No. __/_____, entitled "Lead Frame for Connecting Optical Sub-Assembly to Printed Circuit Board," filed on the same day as the present application, is incorporated herein by reference and includes additional details of the structural features and electrical performance of the lead frame connectors illustrated in the drawings that accompany the present patent application.

2. Lead Frame Connector Fabrication Process

[0028] One of the advantages of the lead frame connectors of the invention is that they can have manufacturing costs that are much lower than the costs of manufacturing flex circuits that have conventionally been used in optical transceiver modules. In addition to the lead frame connectors themselves, the embodiments of the invention also extend to methods of manufacturing the lead frame connectors.

[0029] According to one embodiment, the method of manufacturing lead frame connectors 12 and 22 is performed using a reel-to-reel insert injection molding process. U.S. Patent Application Serial No. __/_____, entitled "Methods of Manufacturing Lead Frame

Connector for Connecting Optical Sub-Assembly to Printed Circuit Board,” filed on the same day as the present application, is incorporated herein by reference and includes additional details of methods of manufacturing the lead frame connectors that can be used to manufacture optical transceiver modules according to the present invention. The foregoing patent application also describes techniques for reducing undesirable RF responses during the process of manufacturing the lead frame connectors 12 and 22.

3. Transceiver Manufacturing Process Using Lead Frame Connectors

[0030] Figures 4a and 4b illustrate opposite sides of a printed circuit board 50 that has lead frame connectors 12 and 22 attached thereto. The invention disclosed herein also extends to methods of manufacturing or assembling optical transceiver modules using the lead frame connectors 12 and 22. According to one embodiment, the method of manufacturing a transceiver module includes a step of connecting the lead frames 12 and 22 to the corresponding optical sub-assemblies 10 and 20. As the process is substantially the same for the ROSA 10 and the TOSA, the processing of only the ROSA is described in detail below.

[0031] The ROSA lead frame connector 12 is aligned with the leads 14 that protrude from the back end of the ROSA. The leads 14 pass through corresponding holes 44 in the ROSA lead frame connector 12 and the leads 14 are soldered to the conductors 34 of the lead frame assembly 12. Passing the leads 14 through the holes 44 in the corresponding electrical contacts 16 can result in substantial self-alignment of the lead frame connector 12 with the optical sub-assembly 10. As shown in Figure 1a, the leads 14 of the ROSA 10 can be conveniently accessed from the opposite side 46 of the lead frame connector 12 to facilitate this soldering process. Once the soldering has been performed, the combined ROSA 10 and

lead frame connector 12 becomes a surface mount device that can then be mounted to the PCB 50.

[0032] The process of surface mounting the combined ROSA 10 and lead frame connector 12 to the PCB 50 can be performed in any of a variety of ways. As shown in Figure 4b, the lead frame connector 12 has an array of leads or pins 18 that are bent in a way that allows them to contact a corresponding array of pads 52 on the PCB 50. As the leads or pins 18 of the lead frame connector 12 are placed in contact with the pads 52, the physical connection is made by hand soldering, by reflow of a solder paste formed on the PCB 50, by a hot bar process, or by any other suitable technique. Another option is to use a fixture that facilitates the process of placing the lead frame connector to the PCB 50 and soldering it thereto.

[0033] It is noted that, according to certain embodiments of the invention, the process of connecting the combined ROSA and lead frame connector to the PCB does not require epoxy reinforcement and avoids alignment handling issues that have been experienced in conventional methods of connecting optical sub-assemblies to PCBs using, for instance, flex circuits.

[0034] The present invention may be embodied in other specific forms without departing from its spirit or essential characteristics. The described embodiments are to be considered in all respects only as illustrative and not restrictive.